
Vented Design DIY Kits





Feature:

- 5" is responsible for the mid-low and the 25mm tweeter is responsible for the high frequency. Each driver handles its own frequency ranges.
- Professional crossover design, using low-loss PP capacitors and oxygen-free copper inductance components
- DIY boxes, great fun of hands on experience by do it yourself
- Environmental- friendly design, the box structure adopts imported wood plates, no paint, no glue for assembly.
- With 50W*2CH amplifier , Class D, Bluetooth 5.0

SYSTEM SPECIFICATION

- PRODUCT NUMBER
- SYSTEM TYPE
- NOMINAL IMPEDANCE
- FREQUENCY RESPONSE(-6dB)
- SENSTIVITY(1M/1W)
- RATED POWER INPUT
- MAXIMUM POWER INPUT
- DRIVER
- AMPLIFIER
- CROSSOVER POINT
- ENCLOSURE STRUCTURE
- NET WEIGHT
- DIMENSIONS/BOX
- PACKING

D52-2A 2.0System 8ohm 40 - 35 K Hz 90 +/- 2dB 30W 60W W5-2143,25-1933S AMH200-100 50W*2CH,CLASS D 3.5K Hz 17mm wood plate 4.85Kg / pc 200 W x269 D x300 H (mm) (10L) Plain Carton



TANG BAND INDUSTRIES CO., LTD

| web | : www.tb-speaker.com |
|--------|-----------------------|
| e-mail | : info@tb-speaker.com |
| tel | : +886-2-2657-0282 |
| fax | : +886-2-2658-0166 |

D52-2A Package include:

- 5"Full range driver 2pcs
- 25mm tweeter 2pcs
- With 50W*2CH amplifier 1pcs
- Instructions Guide
- All wood plates and accessory

D52-2 A